

AC310 Frenleme Direnci Seçim Tablosu

Üç Faz 380V					
Motor gücü (kW)	Direnç (Ω)	değeri	Direnç (W)	gücü	Frenleme torku (%)
0.75 kW	750 Ω		150W		100%
1.5 kW	400 Ω		300W		100%
2.2 kW	250 Ω		400W		100%
4.0 kW	150 Ω		500W		100%
5.5 kW	100 Ω		600W		100%
7.5 kW	75 Ω		780W		100%
11 kW	50 Ω		1.2kW		100%
15 kW	40 Ω		1.5kW		100%
18.5 kW	32 Ω		2.0kW		100%
22 kW	32 Ω		2.0kW		100%
30 kW	24 Ω		3.0kW		100%
37 kW	20 Ω		3.7kW		100%
45 kW	16 Ω		4.5kW		100%
55 kW	13 Ω		5.5kW		100%
75 kW	9.0Ω		7.5kW		100%
90 kW	6.8Ω		9.3kW		100%
110 kW	6.2Ω		11.0kW		100%
132 kW	4.7Ω		13.0kW		100%
160 kW	3.9Ω		15.0kW		100%
185 kW	3.3Ω		17.0kW		100%
200 kW	3.0Ω		18.5kW		100%
220 kW	2.7Ω		20.0kW		100%
250 kW	2.4Ω		22.5kW		100%
280 kW	2.0Ω		25.5kW		100%
315 kW	1.8Ω		30.0kW		100%
355 kW	1.5Ω		33.0kW		100%
400 kW	1.2Ω		42.0kW		100%
450 kW	1.2Ω		42.0kW		100%
500 kW	1.0Ω		42.0kW		100%
560 kW	1.0Ω		50.0kW		100%
630 kW	0.8Ω		60.0kW		100%
710 kW	0.8Ω		70.0kW		100%
Tek Faz 220V					
Motor gücü (kW)	Direnç (Ω)	değeri	Direnç (W)	gücü	Frenleme torku (%)
0.4 kW	400Ω		100W		100%
0.75 kW	200Ω		120W		100%
1.5 kW	100Ω		300W		100%
2.2 kW	75.0Ω		300W		100%
4.0 kW	50.0Ω		500W		100%